Sturt South S418 - User checklist

	Enter the studio and turn everything on
	• Switch lights on as you ontor the first door
	• Switch lights on as you enter the first door.
	 Switch air conditioning on as you enter the second door. There is no natural air flow in
	the room so it gets very hot with the lights on.
	• Use the touch screen panel to start up the system.
	Choose presentation settings on the control panel
	Select presentation style
	 Lectern, free standing or interview (free standing is best)
	 Select presentation behind or logo behind
	 All presentation styles can have a blue background with Uni logo or a
	PowerDoint
	I actors style displays this in the ten right hand corner only with the rest of the
	• Lectern style displays this in the top right hand corner only with the rest of the
	screen blue
	• Select the presentation course
	• Select the presentation source
	 In room PC (can log in for network access or use USB)
	 Personal laptop using HDMI cable in room
	 Tablet using HDMI cable in room
	Set up lapel microphone
	• Turn on the lapel microphone and attach to clothing. Run cables under clothing if
	possible.
	 Test volume on the control panel and using audible 'tap test'
	• Un to 4 people can use the room at once in interview style each using their own
	microphono
	The constant of the second of the second of the second section of the second seco
	• There are no room microphones so if this isn't turned on there will be no sound.
	Set up LISP for recording
	Set up OSB for recording
	• Insert USB into the wall secket below the centrel panel. Danel will show USB has been
	detected when ready
	detected when ready.
	 Check the recording time is enough. Panel will show approximate recording time
	available on the USB (1GB = 1 hour).
	Where to stand during recording
	a like book to show alternation of the finance of the black the section (the finance
	• It's pest to stand immediately in front of the black line on the floor.
	 Do not go behind the black line or come too far forward or you have a green fuzzy hue
	around you in the recording.

Making your recording
 Press the Record/Pause button and wait for the recording time to start counting up. The Record button turns blue. Cot into position and wait a couple more seconds before starting to speak. This makes
• Get into position and wait a couple more seconds before starting to speak. This makes it easier to trim the final video.
 When recording starts, the "on air" light outside comes on.
 Pressing the Record/Pause button will either pause or start the recording again. Press End recording (STOP) when finished
 Press End recording (STOP) when thisned. Before stopping and starting the recording it's advisable to stand still without speaking
for 2-3 seconds each time to make editing the final video much easier.
 There is a short lag before recording stops (approx. 5 seconds) whilst the system finishes writing to the USB drive – do not remove the USB at this point. Always wait until the RECORD button turns grey (i.e. is NOT blue) before removing the USB. You can now press the Record/Pause button to start a new recording using the same settings or press Next step followed by Start another session to use different settings.
Removing the USB
 After the recording has stopped, press Next Step. Can safely remove the USB at this point. Always wait until the RECORD button turns grey (i.e. is NOT blue) before removing the USB.
Shutting everything down when finished
 Turn off lapel microphones and return to the charging dock facing forward. Make sure the red charging light is on before leaving them. Eject USB stick from room PC if used.
 Log off room PC. Remove USB containing the recording from wall socket.
 Press the Shut down button on the control panel to shut the computer and recording lights off.
Put all furniture back where it was found.
Gather all personal items as the room is not secure.
 I urn off air conditioning before leaving main room. Turn off light before entering corridor
 Be careful opening the door to the corridor so as not to hit anyone.
Make sure the door is locked after exiting.